

LED-6000 Series T8 LED Retrofit

Models

LED-6115-4-50K-TFR, 120-277VAC, cULus, 5000K CCT

LED-6115-4-40K-TFR, 120-277VAC, cULus, 4000K CCT



Features

- 18 Watts Replaces up to 32
- Replaces 32W T8 Fluorescent
- >80 CRI
- 50,000 Rated L70 LED life
- UL Classified 1598C
- 5 Year warranty
- Polycarbonate




18W
LED T8

Replaces
32W
T8


Technical Specifications

Models	LED-6115-4-40K-TFR	LED-6115-4-50K-TFR
CCT	4000K	5000K
Power Consumption	18 Watts	
Replaces	32 Watts	
Mounting	G13	
Instant Start Ballast	No	No
Direct Voltage Only (Must Bypass Ballast)	Yes	Yes
Voltage	120-277VAC (USA)	
LED Type	Everlight 2835	
Beam Angle	150° / Omni-Directional	
Dimmable	No	
Operating Temp	-40°F - +122°F	
Rated R70 Life	50,000 Hrs.	
Warranty	5 Year Limited*	
LM79 Specifications	No	No
Power (W)	18	18
CCT (K)	4000	5000
Light Output (lm)	2200	2200
Efficacy (lm/W)	122	122
THD @ 277V	TBD	TBD
PF @ 277V	TBD	TBD
CRI:	>80	>80
R9	TBD	TBD
Duv	TBD	TBD
Packaging	20 Master Carton	
Unit	47.2 X 1.125"	
Master	49.6X 9.8 X 11	

Light Distribution



C180(Max): —
 C0/C180: —
 C90/C270: —



LED Power Consumption (Watts)	HID Power Consumption (Watts)	HID Ballast Power Consumption (Watts)	Total Savings (Watts)	Annual Energy Savings (14 hrs/day)	Lifetime Energy Savings (over 50,000 hrs)
18	26	4	12	\$7	\$66.00

Installation Notes:

Installing LED-6115 series T8 retrofit lamps: **Ballast must be bypassed**

